

12.03.2018

riag Sn 860

Methansulfonate-based bright tin process

The **riag Sn 860** process can be used in both barrel and rack applications as well as in vibration systems. Applications include both decorative and technical purposes.

Properties

- high deposition rates
- bright deposits across a wide current density range
- excellent coat thickness distribution
- excellent solderability of coats
- rack -and barrel application
- technical and decorative application

Make up

	Rack		Barrel / Vibration system	
	Range	Optimum	Range	Optimum
riag Sn 860 Tin	50 – 84 mL/L	67 mL/L	23 – 45 mL/L	33 mL/L
riag Sn 860 Acid	200 – 250 mL/L	210 mL/L	200 – 250 mL/L	220 mL/L
riag Sn 860 Make up	25 mL/L	25 mL/L	10 mL/L	10 mL/L
riag Sn 860 Tenside	100 mL/L	100 mL/L	100 mL/L	100 mL/L
riag Sn 860 Antiox	1.5 g/L	1.5 g/L	1.5 g/L	1.5 g/L

Make up

The tank is filled with deionised water to 50 % of the final volume. While stirring you add the **riag Sn 860 Acid** and the **riag Sn 860 Tin** (Attention: the solution gets warm). As soon as the temperature of the electrolytes has cooled down to 25° C while stirring you add the required amount of **riag Sn 860 Make up**, **riag Sn 860 Tenside** and **riag Sn 860 Antiox** (predissolved). The electrolyte is filled up with water to the final volume. First some dummy parts are coated.

Operating values

	Rack		Barrel / Vibration system	
	Range	Optimum	Range	Optimum
Tin	15 – 25 g/L	20 g/L	7.5 – 15 g/L	10 g/L
riag Sn 860 Acid	200 – 250 mL/L	210 mL/L	200 – 250 mL/L	220 mL/L

Operating parameters

Temperature	22 °C (14 – 25 °C)
Cathodic current density	0.5 – 5.0 A/dm ² in rack applications 0.1 – 2.0 A/dm ² in barrel applications
Anodic current density	1.0 A/dm ² (0.5 – 3.0 A/dm ²)
Current efficiency	< 100 %
Deposit rate	at 2 A/dm ² approx. 1 µm/min.
Anodes	The purity of the tin anodes should at least be 99.99 %. We recommend the use of polypropylene anode bags.
Agitation	Electrolyte agitation by using goods movement at 2 – 5 m/min. required. The filter pump supports the movement and agitation of the electrolyte.
Tanks	Plastic or lined steel
Filtration	For high performance electrolytes constant filtration is necessary. The electrolyte should be circulated two to three times per hour. Especially important in barrel applications in order to ensure the circulation of the electrolyte.
Heating	Thermostatic controlled temperature regulation is essential
Cooling	Usually required, cooling coils of acid resistant plastic or plastic coated steel- or copper tubing, respectively PTFE
Fume extraction	Recommended

Preparation of new tanks	<p>New tanks should be treated with riag Sn 860 Acid 5 % and riag Sn 860 Tenside for 24 hours.</p> <p>When a conversion of the tank from a lead containing electrolyte takes place, an alkaline primary cleaning is recommended. Our sales staff will gladly advise you.</p>				
Maintenance	<p>Analyse and adjust riag Sn 860 Tin and riag Sn 860 Acid as well as riag Sn 860 Antiox regularly. The riag Sn 860 Tin solution contains 300 g/L tin. To increase the tin content of the electrolyte by 1 g/L 3.3 mL/L riag Sn 860 Tin solution are required.</p> <p>Dosage of riag Sn 860 Replenisher and riag Sn 860 Tenside are determined by ampère hours.</p>				
Usage	<p>The additives are used up by drag out as well as electrochemical, that is by anodic or cathodic processes. Therefore the usage may vary process-related.</p> <table border="0" style="margin-top: 10px;"> <tr> <td style="padding-right: 40px;">riag Sn 860 Replenisher</td> <td>3.0 – 5.0 L/10 kWh</td> </tr> <tr> <td>riag Sn 860 Tenside</td> <td>1.5 – 2.5 L/10 kWh</td> </tr> </table>	riag Sn 860 Replenisher	3.0 – 5.0 L/10 kWh	riag Sn 860 Tenside	1.5 – 2.5 L/10 kWh
riag Sn 860 Replenisher	3.0 – 5.0 L/10 kWh				
riag Sn 860 Tenside	1.5 – 2.5 L/10 kWh				
General	<p>In particular the drag-in of chloride into the tin electrolyte has to be avoided. Therefore the parts are activated with riag Sn 860 Acid (approx. 5 % V) instead of hydrochloric acid.</p> <p>Brass and other zinc containing alloys must not at all tin-plated directly since zinc diffuses into the tin coat. In this case a barrier coat of copper or nickel is required. riag Sn 860 Antiox prevents the formation of Sn (IV) and the following clouding of the electrolyte.</p>				

Environmental considerations and product safety

All concentrates, rinse waters and waste solution must be treated and discharged in accordance with local effluent control regulations. Information can be gleaned from the material safety data sheets. Chemicals shall not be stored below 10 °C.

Liability

This instruction manual was compiled with reference to the state of the art and all current standards, and is based on the long-term knowledge and experience of riag. However, riag cannot monitor compliance with this instruction manual and the methods described herein at the customer/end-user's premises. Work carried out with riag products must be adapted accordingly to meet local conditions. In particular, riag cannot accept liability for damage, loss or cost incurred due to a failure to adhere to this instruction manual, improper application of the methods, unauthorised technical modifications, insufficient maintenance or the absence of maintenance in respect of the requisite technical hardware or equipment, or in the event of use by unqualified personnel. riag is not liable for damage or loss caused by riag or its employees except where intention or gross negligence can be proved. riag furthermore reserves the right to make changes in relation to products, methods and the instruction manual without prior notice.

Our goods and services are subject to the General Terms and Conditions for Delivery of the Association of Surface Technology Suppliers (VLO), which can be viewed at www.riag.ch (link "terms and conditions", document "General Terms and Conditions for Delivery", version 3/2018), which we gladly send you on request.

This transaction is governed by material Swiss law (Law of Obligations), excluding private international law (conflict of laws) and intergovernmental treaties, specifically the CISG.

riag Oberflächentechnik AG
Murgstrasse 19a
CH-9545 Wängi
T +41 (0)52 369 70 70
F +41 (0)52 369 70 79
riag.ch
info@riag.ch

Analysis (Analytical Methods)

Sample preparation:

The sample must be taken from a well-mixed point.

Tin (II)

Reagents: Iodine 0.05 mol/L
Hydrochloric acid 37 %
Starch solution 1 %
Calcium carbonate p.a.

Procedure: 5 mL electrolyte are transferred via pipette into a
250 mL beaker, add
50 mL deion. water, add
40 mL hydrochloric acid 37 %, add
approx. 2 g calcium carbonate, add
approx. 2 mL starch solution
Titrate with iodine 0.05 mol/L from colourless to dark blue. The dark blue colour has to stay for 30 s

Calculation: Use in mL x 1.186 = g/L Tin(II)

riag Sn 860 Acid

Reagents: Sodium hydroxide solution 1 mol/L
Methyl red 0.2 % in ethanol

Procedure: 5 mL electrolyte are transferred via pipette into a
100 mL beaker, add
ca. 50 mL deion. water
ca. 3 drops methyl red
Titrate with sodium hydroxide from orange-red to yellow

Calculation: Use in mL x 20.3 = mL/L **riag Sn 860 Acid**